



SMB-T009

Telecomanda radio cu trei butoane, cod saritor, IP54, destinat receptoarelor radio PF009007A

Imagine



YLI ETERNIT ACCES SRL

A.: HAIDUCULUI 3A, CLUJ-NAPOCA

T.: +40 264 484989

W.: www.yli.ro

SMB-T009

Telecomanda radio cu trei butoane, cod saritor, IP54, destinat receptoarelor radio PF009007A

FISA TEHNICA

Descriere

SMB-T009 este o telecomanda radio cu trei butoane, cod saritor, IP54, destinat receptoarelor radio PF009007A.

Datorita codarii sale criptate cu cod saritor si cu functie anti-copiere, ofera servicii de incredere chiar si intr-un mediu nesigur.

Garniturile butoanelor pot fi usor inlocuite, in pachet vin incluse trei garnituri de culori diferite.

Caracteristici

- Receptoare compatibile PF009007A
- Cod saritor (criptat)
- Garnituri butoane inlocuibile

Specificatii

- Alimentare: 12Vcc (baterie LR23A)
- Consum functionare: 20mA
- Consum stand-by: <1uA
- Cod: Saritor
- Frecventa: 433.92MHz
- Putere de transmisie: <20dBm
- Raza de actiune: <100m (in camp deschis)
<30m (in cladiri)
- Numar butoane: 3
- Feedback: LED (rosu)
- Material: ABS
- Culoare: Negru
- Protectie la intemperii: IP54
- Temperatura de functionare: -20°C ~ +60°C
- Dimensiuni: 67(L) x 33(l) x 15(A)mm
- Greutate: 0.025kg

Observatii



EEE FAC OBIECTUL UNEI
COLECTARI SEPARATE

